

SANYO

No.1421A

2SA1338/2SC3392

PNP/NPN Epitaxial Planar Silicon Transistors

High-Speed Switching Applications

Features

- Adoption of FBET process
- High breakdown voltage: $V_{CEO} = (-) 50V$
- Large current capacity and high f_T
- Very small-sized package permitting sets to be small-sized, slim

(): 2SA1338

Absolute Maximum Ratings at $T_a = 25^\circ C$

			unit
Collector to Base Voltage	V_{CBO}	(-) 60	V
Collector to Emitter Voltage	V_{CEO}	(-) 50	V
Emitter to Base Voltage	V_{EBO}	(-) 5	V
Collector Current	I_C	(-) 500	mA
Collector Current(Pulse)	I_{CP}	(-) 800	mA
Collector Dissipation	P_C	200	mW
Junction Temperature	T_j	150	$^\circ C$
Storage Temperature	T_{stg}	-55 to +150	$^\circ C$


Electrical Characteristics at $T_a = 25^\circ C$

			min	typ	max	unit
Collector Cutoff Current	I_{CBO}	$V_{CB} = (-) 40V, I_E = 0$			(-) 0.1	μA
Emitter Cutoff Current	I_{EBO}	$V_{EB} = (-) 4V, I_C = 0$			(-) 0.1	μA
DC Current gain	h_{FE}	$V_{CE} = (-) 5V, I_C = (-) 10mA$	100*		560*	
Gain-Bandwidth Product	f_T	$V_{CE} = (-) 10V, I_C = (-) 50mA$		300 (200)		MHz
Output Capacitance	c_{ob}	$V_{CB} = (-) 10V, f = 1MHz$		3.7 (5.6)		pF
C-E Saturation Voltage	$V_{CE(sat)}$	$I_C = (-) 100mA, I_B = (-) 10mA$		0.1 (0.15)	0.3 (0.4)	V
B-E Saturation Voltage	$V_{BE(sat)}$	$I_C = (-) 100mA, I_B = (-) 10mA$		0.8	1.2	V
C-B Breakdown Voltage	$V_{(BR)CBO}$	$I_C = (-) 10\mu A, I_E = 0$	(-) 60			V
C-E Breakdown Voltage	$V_{(BR)CEO}$	$I_C = (-) 100\mu A, R_{BE} = \infty$	(-) 50			V
E-B Breakdown Voltage	$V_{(BR)EBO}$	$I_E = (-) 10\mu A, I_C = 0$	(-) 5			V
Turn-on Time	t_{on}	$V_{CC} = 20V,$		70 (70)		ns
Storage Time	t_{stg}	$I_C = 10I_{B1} = -10I_{B2} = 100mA$	400 (400)			ns
Fall Time	t_f			70 (50)		ns

* : The 2SA1338/2SC3392 are classified by 10mA h_{FE} as follows:


2SA1338/ 2SC3392	100	4	200	140	5	280
	200	6	400	280	7	560

(Note) 2SA1338 marking:AL/2SC3392 marking:AY

 h_{FE} rank: 4, 5, 6, 7Package Dimensions 2018A
(unit:mm)**SANYO Electric Co., Ltd. Semiconductor Business Headquarters**







TOKYO OFFICE Tokyo Bldg., 1-10, 1 Chome, Ueno, Taito-ku, TOKYO, 110 JAPAN

Switching Time Test Circuit

















(For PNP, the polarity is reversed.)

Unit (Resistance : Ω, Capacitance : F)



2SA1338/2SC3392





■ No products described or contained herein are intended for use in surgical implants, life-support systems, aerospace equipment, nuclear power control systems, vehicles, disaster/crime-prevention equipment and the like, the failure of which may directly or indirectly cause injury, death or property loss.

■ Anyone purchasing any products described or contained herein for an above-mentioned use shall:

- ① Accept full responsibility and indemnity and defend SANYO ELECTRIC CO., LTD., its affiliates, subsidiaries and distributors and all their officers and employees, jointly and severally, against any and all claims and litigation and all damages, cost and expenses associated with such use;
- ② Not impose any responsibility for any fault or negligence which may be cited in any such claim or litigation on SANYO ELECTRIC CO., LTD., its affiliates, subsidiaries and distributors or any of their officers and employees jointly or severally.

■ Information (including circuit diagrams and circuit parameters) herein is for example only; it is not guaranteed for volume production. SANYO believes information herein is accurate and reliable, but no guarantees are made or implied regarding its use or any infringements of intellectual property rights or other rights of third parties.