

# FDZ3N513ZT

## Integrated NMOS and Schottky Diode

### Features


- Monolithic NMOS and Schottky Diode
- Ultra-small form factor 1mm x 1mm WLCSP
- Max  $r_{DS(on)}$  = 462 mΩ at  $V_{GS} = 4.5$  V,  $I_D = 0.3$  A
- Max  $r_{DS(on)}$  = 520 mΩ at  $V_{GS} = 3.2$  V,  $I_D = 0.3$  A
- HBM ESD protection level > 2000V (Note3)
- RoHS Compliant

### General Description


The FDZ3N513ZT is a monolithic NMOS/ Schottky combination (FETky) and is designed and wired to function as a discontinuous conduction mode (DCM) boost LED power train for mobile LED backlighting applications.

### Application


- Boost Converter Power Train for single cell Li-ion LED backlighting



WL-CSP 3D Bumps Facing Up View



WL-CSP 3D Bumps Facing Down View



WL-CSP 1.0X1.0 Bumps Facing Up View

### Absolute Maximum Ratings

Symbol	Parameter	Ratings	Units
$V_{DS}$	NMOS Drain to Source Voltage	30	V
$V_{GS}$	NMOS Gate to Source Voltage	-0.3/5.5	V
$P_D$	Power Dissipation @ $T_A = 25^\circ\text{C}$ (Note 1a)	1	W
$I_D$	Maximum Continuous NMOS Drain Current (Note 1a)	1.1	A
$V_{RRM}$	Schottky Repetitive Peak Reverse Voltage	25	V
$I_O$	Schottky Average Forward Current	0.3	A
$T_J, T_{STG}$	Operating Junction and Storage Temperature	-55/125	$^\circ\text{C}$
ESD	Electrostatic Discharge Protection	CDM 2000	V

### Thermal Characteristics

$R_{\theta JA}$	Thermal Resistance, Junction to Ambient - 1in <sup>2</sup> , 2oz. Copper (Note 1a)	100	$^\circ\text{C/W}$
$R_{\theta JA}$	Thermal Resistance, Junction to Ambient - Minimum Pad (Note 1b)	260	$^\circ\text{C/W}$

### Package Marking and Ordering Information

Part Number	Device Marking	Package	Reel Size	Tape Width	Quantity
FDZ3N513ZT	Z3	WL-CSP 1.0X1.0	7"	8mm	5000 units

## Electrical Characteristics $T_J = 25\text{ }^\circ\text{C}$ unless otherwise noted

Symbol	Parameter	Test Conditions	Min	Typ	Max	Units
--------	-----------	-----------------	-----	-----	-----	-------

### Off Characteristics

$BV_{DSS}$	Drain to Source Breakdown Voltage	$I_D = 250\text{ }\mu\text{A}$ , $V_{GS} = 0\text{ V}$	30			V
$\frac{\Delta BV_{DSS}}{\Delta T_J}$	Breakdown Voltage Temperature Coefficient	$I_D = 250\text{ }\mu\text{A}$ , referenced to $25\text{ }^\circ\text{C}$		47		mV/ $^\circ\text{C}$
$I_{DSS}$	Zero Gate Voltage Drain Current	$V_{DS} = 24\text{ V}$ , $V_{GS} = 0\text{ V}$			1	$\mu\text{A}$
$I_{GSS}$	Gate to Source Leakage Current	$V_{GS} = +5\text{ V}/-0.3\text{ V}$ , $V_{DS} = 0\text{ V}$			$\pm 10$	$\mu\text{A}$

### On Characteristics

$V_{GS(th)}$	Gate to Source Threshold Voltage	$V_{GS} = V_{DS}$ , $I_D = 250\text{ }\mu\text{A}$	0.5	0.7	1.5	V
$\frac{\Delta V_{GS(th)}}{\Delta T_J}$	Gate to Source Threshold Voltage Temperature Coefficient	$I_D = 250\text{ }\mu\text{A}$ , referenced to $25\text{ }^\circ\text{C}$		-1.6		mV/ $^\circ\text{C}$
$r_{DS(on)}$	Drain to Source On Resistance	$V_{GS} = 4.5\text{ V}$ , $I_D = 0.3\text{ A}$ $V_{GS} = 3.2\text{ V}$ , $I_D = 0.3\text{ A}$		384 410	462 520	m $\Omega$
$g_{FS}$	Forward Transconductance	$V_{DS} = 5\text{ V}$ , $I_D = 0.3\text{ A}$		0.5		S

### Dynamic Characteristics

$C_{iss}$	Input Capacitance	$V_{DS} = 15\text{ V}$ , $V_{GS} = 0\text{ V}$ , $f = 1\text{ MHz}$		45	85	pF
$C_{oss}$	Output Capacitance			45	85	pF
$C_{rss}$	Reverse Transfer Capacitance			10	25	pF
$R_g$	Gate Resistance			2.0		$\Omega$

### Switching Characteristics

$t_{d(on)}$	Turn-On Delay Time	$V_{DD} = 15\text{ V}$ , $I_D = 0.3\text{ A}$ $V_{GS} = 5\text{ V}$ , $R_{GEN} = 6\text{ }\Omega$		3.1	10	ns
$t_r$	Rise Time			1.9	10	ns
$t_{d(off)}$	Turn-Off Delay Time			9.6	20	ns
$t_f$	Fall Time			2.7	10	ns
$Q_g$	Total Gate Charge ( $V_{GS} = 4.5\text{ V}$ )		$V_{DD} = 15\text{ V}$ $I_D = 0.3\text{ A}$		1.0	
$Q_{gs}$	Gate to Source Gate Charge			0.1		nC
$Q_{gd}$	Gate to Drain "Miller" Charge			0.3		nC

### Drain-Source Diode Characteristics


$V_{SD}$	Source to Drain Diode Forward Voltage	$V_{GS} = 0\text{ V}$ , $I_S = 0.3\text{ A}$ (Note 2)		0.75	1.2	V
$t_{rr}$	Reverse Recovery Time	$I_F = 0.3\text{ A}$ , $di/dt = 100\text{ A}/\mu\text{s}$		16	29	ns
$Q_{rr}$	Reverse Recovery Charge			6.0	10	nC

### Schottky Diode Characteristics

$I_R$	Reverse Leakage	$V_R = 20\text{ V}$	$T_J = 25\text{ }^\circ\text{C}$		15	30	$\mu\text{A}$
			$T_J = 85\text{ }^\circ\text{C}$		300		$\mu\text{A}$
$V_F$	Forward Voltage	$I_F = 300\text{ mA}$	$T_J = 25\text{ }^\circ\text{C}$		0.72	1.2	V
			$T_J = 85\text{ }^\circ\text{C}$		0.74		

#### Notes:

1.  $R_{\theta JA}$  is determined with the device mounted on a  $1\text{ in}^2$  oz. copper pad on a  $1.5 \times 1.5\text{ in.}$  board of FR-4 material.  $R_{\theta JC}$  is guaranteed by design while  $R_{\theta JA}$  is determined by the user's board design.



a.  $100\text{ }^\circ\text{C}/\text{W}$  when mounted on a  $1\text{ in}^2$  pad of 2 oz copper.



b.  $260\text{ }^\circ\text{C}/\text{W}$  when mounted on a minimum pad of 2 oz copper.

2. Pulse Test: Pulse Width <  $300\mu\text{s}$ , Duty cycle < 2.0%.

3. The diode connected between the gate and source serves only as protection ESD. No gate overvoltage rating is implied.

**Typical Characteristics**  $T_J = 25^\circ\text{C}$  unless otherwise noted




Figure 1. On Region Characteristics




Figure 2. Normalized On-Resistance vs Drain Current and Gate Voltage




Figure 3. Normalized On Resistance vs Junction Temperature




Figure 4. On-Resistance vs Gate to Source Voltage




Figure 5. Transfer Characteristics






Figure 6. Source to Drain Diode Forward Voltage vs Source Current


**Typical Characteristics**  $T_J = 25^\circ\text{C}$  unless otherwise noted




**Figure 7. Gate Charge Characteristics**




**Figure 8. Capacitance vs Drain to Source Voltage**




**Figure 9. Forward Bias Safe Operating Area**



**Figure 10. Gate Leakage Current vs Gate to Source Voltage**




**Figure 11. Schottky Diode Reverse Current**




**Figure 12. Schottky Diode Forward Voltage**

**Typical Characteristics**  $T_J = 25^\circ\text{C}$  unless otherwise noted




**Figure 13. Single Pulse Maximum Power Dissipation**




**Figure 14. Junction-to-Ambient Transient Thermal Response Curve**


## Dimensional Outline and Pad Layout




TOP VIEW



RECOMMENDED LAND PATTERN  
(NSMD PAD TYPE)



SIDE VIEWS



BOTTOM VIEW

### NOTES:

- A. NO JEDEC REGISTRATION APPLIES.
- B. DIMENSIONS ARE IN MILLIMETERS.
- C. DIMENSIONS AND TOLERANCES PER ASME Y14.5M, 1994.
- D.** DATUM C IS DEFINED BY THE SPHERICAL CROWNS OF THE BALLS.
- E. PACKAGE NOMINAL HEIGHT IS 582 MICRONS ±43 MICRONS (539-625 MICRONS).
- F.** FOR DIMENSIONS D, E, X, AND Y SEE PRODUCT DATASHEET.






### Product Specific Dimensions

Product	D	E	X	Y
FDZ3N513ZTUCX	1.000 +/-0.030	1.000 +/-0.030	0.018	0.018



**TRADEMARKS**

The following includes registered and unregistered trademarks and service marks, owned by Fairchild Semiconductor and/or its global subsidiaries, and is not intended to be an exhaustive list of all such trademarks.

- |   |   |   |   |
|---|---|---|---|
| AccuPower™  | F-PFS™  | Power-SPM™  |  <b>SYSTEM GENERAL</b> ®<br>The Power Franchise®<br>the <b>power</b> franchise<br>TinyBoost™<br>TinyBuck™<br>TinyCalc™<br>TinyLogic®<br>TINYOPTO™<br>TinyPower™<br>TinyPWM™<br>TinyWire™<br>TriFault Detect™<br>TRUECURRENT™*<br>μSerDes™<br> SerDes®<br>UHC®<br>Ultra FRFET™<br>UniFET™<br>VCX™<br>VisualMax™<br>XS™ |
| Auto-SPM™   | FRFET®  | PowerTrench®  |   |
| Build it Now™   | Global Power Resource <sup>SM</sup>   | PowerXST™   |   |
| CorePLUS™   | Green FPS™  | Programmable Active Droop™  |   |
| CorePOWER™  | Green FPS™ e-Series™  | QFET®   |   |
| CROSSVOLT™  | Gmax™   | QS™   |   |
| CTL™  | GTO™  | Quiet Series™   |   |
| Current Transfer Logic™   | IntelliMAX™   | RapidConfigure™   |   |
| DEUXPEED®   | ISOPLANAR™  |  ™ |   |
| Dual Cool™  | MegaBuck™   | Saving our world, 1mW/W/kW at a time™   |   |
| EcoSPARK®   | MICROCOUPLER™   | SignalWise™   |   |
| EfficientMax™   | MicroFET™   | SmartMax™   |   |
| ESBC™   | MicroPak™   | SMART START™  |   |
|  ™ | MicroPak2™  | SPM®  |   |
| Fairchild®  | MillerDrive™  | STEALTH™  |   |
| Fairchild Semiconductor®  | MotionMax™  | SuperFET™   |   |
| FACT Quiet Series™  | Motion-SPM™   | SuperSOT™-3   |   |
| FACT®   | OptoHiT™  | SuperSOT™-6   |   |
| FAST®   | OPTOLOGIC®  | SuperSOT™-8   |   |
| FastvCore™  | OPTOPLANAR®   | SupreMOS™   |   |
| FETBench™   |  ™ | SyncFET™  |   |
| FlashWriter®*   |   | Sync-Lock™  |   |
| FPS™  | PDP SPM™  |   |   |

\* Trademarks of System General Corporation, used under license by Fairchild Semiconductor.

**DISCLAIMER**

FAIRCHILD SEMICONDUCTOR RESERVES THE RIGHT TO MAKE CHANGES WITHOUT FURTHER NOTICE TO ANY PRODUCTS HEREIN TO IMPROVE RELIABILITY, FUNCTION, OR DESIGN. FAIRCHILD DOES NOT ASSUME ANY LIABILITY ARISING OUT OF THE APPLICATION OR USE OF ANY PRODUCT OR CIRCUIT DESCRIBED HEREIN; NEITHER DOES IT CONVEY ANY LICENSE UNDER ITS PATENT RIGHTS, NOR THE RIGHTS OF OTHERS. THESE SPECIFICATIONS DO NOT EXPAND THE TERMS OF FAIRCHILD'S WORLDWIDE TERMS AND CONDITIONS, SPECIFICALLY THE WARRANTY THEREIN, WHICH COVERS THESE PRODUCTS.

**LIFE SUPPORT POLICY**

FAIRCHILD'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF FAIRCHILD SEMICONDUCTOR CORPORATION.

As used herein:

- Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body or (b) support or sustain life, and (c) whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in a significant injury of the user.
- A critical component in any component of a life support, device, or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.

**ANTI-COUNTERFEITING POLICY**

Fairchild Semiconductor Corporation's Anti-Counterfeiting Policy. Fairchild's Anti-Counterfeiting Policy is also stated on our external website, [www.fairchildsemi.com](http://www.fairchildsemi.com), under Sales Support.

Counterfeiting of semiconductor parts is a growing problem in the industry. All manufacturers of semiconductor products are experiencing counterfeiting of their parts. Customers who inadvertently purchase counterfeit parts experience many problems such as loss of brand reputation, standard performance, failed applications, and increased cost of production and manufacturing delays. Fairchild is taking strong measures to protect ourselves and our customers from the proliferation of counterfeit parts. Fairchild strongly encourages customers to purchase Fairchild parts either directly from Fairchild or from Authorized Fairchild Distributors who are listed by country on our web page cited above. Products customers buy either from Fairchild directly or from Authorized Fairchild Distributors are genuine parts, have full traceability, meet Fairchild's quality standards for handling and storage and provide access to Fairchild's full range of up-to-date technical and product information. Fairchild and our Authorized Distributors will stand behind all warranties and will appropriately address any warranty issues that may arise. Fairchild will not provide any warranty coverage or other assistance for parts bought from Unauthorized Sources. Fairchild is committed to combat this global problem and encourage our customers to do their part in stopping this practice by buying direct or from authorized distributors.

**PRODUCT STATUS DEFINITIONS**

**Definition of Terms**

Datasheet Identification	Product Status	Definition
Advance Information	Formative / In Design	Datasheet contains the design specifications for product development. Specifications may change in any manner without notice.
Preliminary	First Production	Datasheet contains preliminary data; supplementary data will be published at a later date. Fairchild Semiconductor reserves the right to make changes at any time without notice to improve design.
No Identification Needed	Full Production	Datasheet contains final specifications. Fairchild Semiconductor reserves the right to make changes at any time without notice to improve the design.
Obsolete	Not In Production	Datasheet contains specifications on a product that is discontinued by Fairchild Semiconductor. The datasheet is for reference information only.

Rev. I48