




# STP6NK90Z - STP6NK90ZFP STB6NK90Z

N-CHANNEL 900V - 1.56Ω - 5.8A TO-220/TO-220FP/D<sup>2</sup>PAK  
Zener-Protected SuperMESH™ Power MOSFET

TYPE	V <sub>DSS</sub>	R <sub>DS(on)</sub>	I <sub>D</sub>	P <sub>w</sub>
STP6NK90Z	900 V	<2 Ω	5.8 A	140 W
STP6NK90ZFP	900 V	<2 Ω	5.8 A	30 W
STB6NK90Z	900 V	<2 Ω	5.8 A	140 W

- TYPICAL R<sub>DS(on)</sub> = 1.56 Ω
- EXTREMELY HIGH dv/dt CAPABILITY
- 100% AVALANCHE TESTED
- GATE CHARGE MINIMIZED
- VERY LOW INTRINSIC CAPACITANCES
- VERY GOOD MANUFACTURING REPEATABILITY




## DESCRIPTION

The SuperMESH™ series is obtained through an extreme optimization of ST's well established strip-based PowerMESH™ layout. In addition to pushing on-resistance significantly down, special care is taken to ensure a very good dv/dt capability for the most demanding applications. Such series complements ST full range of high voltage MOSFETs including revolutionary MDmesh™ products.

## APPLICATIONS

- HIGH CURRENT, HIGH SPEED SWITCHING
- IDEAL FOR OFF-LINE POWER SUPPLIES, ADAPTORS AND PFC
- LIGHTING

## INTERNAL SCHEMATIC DIAGRAM



## ORDERING INFORMATION

SALES TYPE	MARKING	PACKAGE	PACKAGING
STP6NK90Z	P6NK90Z	TO-220	TUBE
STP6NK90ZFP	P6NK90ZFP	TO-220FP	TUBE
STB6NK90ZT4	B6NK90Z	D <sup>2</sup> PAK	TAPE & REEL

## STP6NK90Z - STP6NK90ZFP - STB6NK90Z

### ABSOLUTE MAXIMUM RATINGS

Symbol	Parameter	Value		Unit
		STP6NK90Z / STB6NK90Z	STP6NK90ZFP	
$V_{DS}$	Drain-source Voltage ( $V_{GS} = 0$ )	900		V
$V_{DGR}$	Drain-gate Voltage ( $R_{GS} = 2\text{ k}\Omega$ )	900		V
$V_{GS}$	Gate-source Voltage	$\pm 30$		V
$I_D$	Drain Current (continuous) at $T_C = 25^\circ\text{C}$	5.8	5.8 (*)	A
$I_D$	Drain Current (continuous) at $T_C = 100^\circ\text{C}$	3.65	3.65 (*)	A
$I_{DM} (\bullet)$	Drain Current (pulsed)	23.2	23.2 (*)	A
$P_{TOT}$	Total Dissipation at $T_C = 25^\circ\text{C}$	140	30	W
	Derating Factor	1.12	0.24	W/ $^\circ\text{C}$
$V_{ESD(G-S)}$	Gate source ESD(HBM-C=100pF, R=1.5K $\Omega$ )	4000		V
$dv/dt$ (1)	Peak Diode Recovery voltage slope	4.5		V/ns
$V_{iso}$	Insulation Withstand Voltage (DC)	--	2500	V
$T_j$ $T_{stg}$	Operating Junction Temperature Storage Temperature	-55 to 150		$^\circ\text{C}$

(•) Pulse width limited by safe operating area

(1)  $I_{SD} \leq 5.8\text{A}$ ,  $di/dt \leq 200\text{A}/\mu\text{s}$ ,  $V_{DD} \leq V_{(BR)DSS}$ ,  $T_j \leq T_{JMAX}$ .

(\*) Limited only by maximum temperature allowed

### THERMAL DATA

		TO-220	D <sup>2</sup> PAK	TO-220FP	Unit
$R_{thj-case}$	Thermal Resistance Junction-case Max	0.89		4.2	$^\circ\text{C/W}$
$R_{thj-pcb}$	Thermal Resistance Junction-pcb Max (When mounted on minimum Footprint)		60		$^\circ\text{C/W}$
$R_{thj-amb}$	Thermal Resistance Junction-ambient Max	62.5			$^\circ\text{C/W}$
$T_I$	Maximum Lead Temperature For Soldering Purpose	300			$^\circ\text{C}$

### AVALANCHE CHARACTERISTICS

Symbol	Parameter	Max Value	Unit
$I_{AR}$	Avalanche Current, Repetitive or Not-Repetitive (pulse width limited by $T_j$ max)	5.8	A
$E_{AS}$	Single Pulse Avalanche Energy (starting $T_j = 25^\circ\text{C}$ , $I_D = I_{AR}$ , $V_{DD} = 5\text{ V}$ )	300	mJ

### GATE-SOURCE ZENER DIODE

Symbol	Parameter	Test Conditions	Min.	Typ.	Max.	Unit
$BV_{GSO}$	Gate-Source Breakdown Voltage	$I_{GS} = \pm 1\text{mA}$ (Open Drain)	30			V

### PROTECTION FEATURES OF GATE-TO-SOURCE ZENER DIODES

The built-in back-to-back Zener diodes have specifically been designed to enhance not only the device's ESD capability, but also to make them safely absorb possible voltage transients that may occasionally be applied from gate to source. In this respect the Zener voltage is appropriate to achieve an efficient and cost-effective intervention to protect the device's integrity. These integrated Zener diodes thus avoid the usage of external components.

**ELECTRICAL CHARACTERISTICS (T<sub>CASE</sub> =25°C UNLESS OTHERWISE SPECIFIED)**  
ON/OFF

Symbol	Parameter	Test Conditions	Min.	Typ.	Max.	Unit
V(BR)DSS	Drain-source Breakdown Voltage	I <sub>D</sub> = 1mA, V <sub>GS</sub> = 0	900			V
I <sub>DSS</sub>	Zero Gate Voltage Drain Current (V <sub>GS</sub> =0 )	V <sub>DS</sub> = Max Rating V <sub>DS</sub> = Max Rating, T <sub>C</sub> = 125 °C			1 50	μA μA
I <sub>GSS</sub>	Gate-body Leakage Current (V <sub>DS</sub> =0 )	V <sub>GS</sub> = ± 20V			±10	μA
V <sub>GS(th)</sub>	Gate Threshold Voltage	V <sub>DS</sub> = V <sub>GS</sub> , I <sub>D</sub> = 100μA	3	3.75	4.5	V
R <sub>DS(on)</sub>	Static Drain-source On Resistance	V <sub>GS</sub> =1 0V, I <sub>D</sub> = 2.9 A		1.56	2	Ω

**DYNAMIC**

Symbol	Parameter	Test Conditions	Min.	Typ.	Max.	Unit
g <sub>f</sub> (1)	Forward Transconductance	V <sub>DS</sub> =15V, I <sub>D</sub> =2 .9A		5		S
C <sub>iss</sub> C <sub>oss</sub> C <sub>rss</sub>	Input Capacitance Output Capacitance Reverse Transfer Capacitance	V <sub>DS</sub> = 25V,f= 1M Hz,V <sub>GS</sub> = 0		1350 130 26		pF pF pF
C <sub>oss eq. (3)</sub>	Equivalent Output Capacitance	V <sub>GS</sub> =0 V, V <sub>DS</sub> = 0V to 720V		70		pF

**SWITCHING ON**

Symbol	Parameter	Test Conditions	Min.	Typ.	Max.	Unit
t <sub>d(on)</sub> t <sub>r</sub>	Turn-on Delay Time Rise Time	V <sub>DD</sub> =4 50V , I <sub>D</sub> =3 A R <sub>G</sub> = 4.7Ω ,V <sub>GS</sub> =1 0V (Resistive Load see, Figure 3)		17 20		ns ns
Q <sub>g</sub> Q <sub>gs</sub> Q <sub>gd</sub>	Total Gate Charge Gate-Source Charge Gate-Drain Charge	V <sub>DD</sub> =7 20V , I <sub>D</sub> = 5.8 A, V <sub>GS</sub> =1 0V		46.5 8.5 25		nC nC nC

**SWITCHING OFF**

Symbol	Parameter	Test Conditions	Min.	Typ.	Max.	Unit
t <sub>d(off)</sub> t <sub>f</sub>	Turn-off Delay Time Fall Time	V <sub>DD</sub> = 450 V, I <sub>D</sub> =3 A R <sub>G</sub> =4 .7Ω ,V <sub>GS</sub> =1 0 V (Resistive Load see, Figure 3)		45 20		ns ns
t <sub>r(Voff)</sub> t <sub>f</sub> t <sub>c</sub>	Off-voltage Rise Time Fall Time Cross-over Time	V <sub>DD</sub> = 720V, I <sub>D</sub> = 5.8 A, R <sub>G</sub> =4 .7Ω ,V <sub>GS</sub> =1 0V (Inductive Load see, Figure 5)		11 12 20		ns ns ns

**SOURCE DRAIN DIODE**

Symbol	Parameter	Test Conditions	Min.	Typ.	Max.	Unit
I <sub>SD</sub> I <sub>SDM (2)</sub>	Source-drain Current Source-drain Current (pulsed)				5.8 23.2	A A
V <sub>SD (1)</sub>	Forward On Voltage	I <sub>SD</sub> = 5.8 A, V <sub>GS</sub> =0			1.6	V
t <sub>rr</sub> Q <sub>rr</sub> I <sub>RRM</sub>	Reverse Recovery Time Reverse Recovery Charge Reverse Recovery Current	I <sub>SD</sub> = 5.8 A, di/dt = 100A/μs V <sub>DD</sub> =3 6V, T <sub>j</sub> = 150°C (see test circuit, Figure 5)		840 5880 14		ns nC A


Note: 1. Pulsed: Pulse duration = 300 μs, duty cycle 1.5 %.

2. Pulse width limited by safe operating area.


3. C<sub>oss eq.</sub> is defined as a constant equivalent capacitance giving the same charging time as C<sub>oss</sub> when V<sub>DS</sub> increases from 0 to 80% V<sub>DSS</sub>.

## STP6NK90Z - STP6NK90ZFP - STB6NK90Z


### Safe Operating Area For TO-220/D2PAK




### Safe Operating Area For TO-220FP




### Thermal Impedance For TO-220/D2PAK




### Output Characteristics




### Thermal Impedance For TO-220FP




### Transfer Characteristics




**Transconductance**




**Static Drain-source On Resistance**




**Gate Charge vs Gate-source Voltage**




**Capacitance Variations**



**Normalized Gate Threshold Voltage vs Temp.**




**Normalized On Resistance vs Temperature**




## STP6NK90Z - STP6NK90ZFP - STB6NK90Z

---


### Source-drain Diode Forward Characteristics




### Normalized BVDSS vs Temperature




### Maximum Avalanche Energy vs Temperature




**Fig. 1:** Unclamped Inductive Load Test Circuit




**Fig. 2:** Unclamped Inductive Waveform




**Fig. 3:** Switching Times Test Circuit For Resistive Load



**Fig. 4:** Gate Charge test Circuit





**Fig. 5:** Test Circuit For Inductive Load Switching And Diode Recovery Times



**TO-220 MECHANICAL DATA**


DIM.	mm			inch		
	MIN.	TYP.	MAX.	MIN.	TYP.	MAX.
A	4.40	4.	60	0.173		0.181
C	1.23	1.	32	0.048		0.051
D	2.40	2.	72	0.094		0.107
D1	1.27				0.050	
E	0.49	0.	70	0.019		0.027
F	0.61	0.	88	0.024		0.034
F1	1.14	1.	70	0.044		0.067
F2	1.14	1.	70	0.044		0.067
G	4.95	5.	15	0.194		0.203
G1	2.4		2.7	0.094	0.1	0.6
H2	10.0		10.40	0.393	0.4	0.9
L2	16.4				0.645	
L4	13.0		14.0	0.511	0.5	51
L5	2.65	2.	95	0.104		0.116
L6	15.25	1	5.75	0.600		0.620
L7	6.2		6.6	0.244	0.2	60
L9	3.5	3.	93	0.137		0.154
DIA.	3.75	3.	85	0.147		0.151



P011C


## TO-220FP MECHANICAL DATA



DIM.	mm.			inch		
	MIN.	TYP.	MAX.	MIN.	TYP.	MAX.
A	4.4		4.6	0.173		0.181
B	2.5		2.7	0.098		0.106
D	2.5		2.75	0.098		0.108
E	0.45		0.7	0.017		0.027
F	0.75		1	0.030		0.039
F1	1.15		1.5	0.045		0.067
F2	1.15		1.5	0.045		0.067
G	4.95		5.2	0.195		0.204
G1	2.4		2.7	0.094		0.106
H	10		10.4	0.393		0.409
L2		16			0.630	
L3	28.6		30.6	1.126		1.204
L4	9.8		10.6	.0385		0.417
L5	2.9		3.6	0.114		0.141
L6	15.9		16.4	0.626		0.645
L7	9		9.3	0.354		0.366
Ø	3		3.2	0.118		0.126



**D<sup>2</sup>PAK MECHANICAL DATA**

DIM.	mm.			inch		
	MIN.	TYP.	MAX.	MIN.	TYP.	MAX.
A	4.4		4.6	0.173		0.181
A1	2.49		2.69	0.098		0.106
A2	0.03		0.23	0.001		0.009
B	0.7		0.93	0.027		0.036
B2	1.14		1.7	0.044		0.067
C	0.45		0.6	0.017		0.023
C2	1.23		1.36	0.048		0.053
D	8.95		9.35	0.352		0.368
D1		8			0.315	
E	10		10.4	0.393		
E1		8.5			0.334	
G	4.88		5.28	0.192		0.208
L	15		15.85	0.590		0.625
L2	1.27		1.4	0.050		0.055
L3	1.4		1.75	0.055		0.068
M	2.4		3.2	0.094		0.126
R		0.4			0.015	
V2	0°		4°			



**D<sup>2</sup>PAK FOOTPRINT****TUBE SHIPMENT (no suffix)\*****TAPE AND REEL SHIPMENT (suffix "T4")\***

\* on sales type



## **STP6NK90Z - STP6NK90ZFP - STB6NK90Z**

---

Information furnished is believed to be accurate and reliable. However, STMicroelectronics assumes no responsibility for the consequences of use of such information nor for any infringement of patents or other rights of third parties which may result from its use. No license is granted by implication or otherwise under any patent or patent rights of STMicroelectronics. Specifications mentioned in this publication are subject to change without notice. This publication supersedes and replaces all information previously supplied. STMicroelectronics products are not authorized for use as critical components in life support devices or systems without express written approval of STMicroelectronics.

© The ST logo is a registered trademark of STMicroelectronics

© 2003 STMicroelectronics - Printed in Italy - All Rights Reserved  
STMicroelectronics GROUP OF COMPANIES

Australia - Brazil - Canada - China - Finland - France - Germany - Hong Kong - India - Israel - Italy - Japan - Malaysia - Malta - Morocco  
Singapore - Spain - Sweden - Switzerland - United Kingdom - United States.

© <http://www.st.com>